

New Jersey Semi-Conductor Products, Inc.

20 STERN AVE.
SPRINGFIELD, NEW JERSEY 07081
U.S.A.

TELEPHONE: (973) 376-2922
(212) 227-6005
FAX: (973) 376-8960

Triacs Bidirectional Triode Thyristors

... designed primarily for industrial and military applications for the control of ac loads in applications such as light dimmers, power supplies, heating controls, motor controls, welding equipment and power switching systems;

- All Diffused and Glass Passivated Junctions for Greater Stability
- Pressfit, Stud and Isolated Stud Packages
- Gate Triggering Guaranteed In All 3 Quadrants

MAXIMUM RATINGS


Rating	Symbol	Value	Unit
Repetitive Peak Off-State Voltage ($T_C = -40^\circ\text{C}$ to $+115^\circ\text{C}$) SC260B, SC260B3, SC261B SC260D, SC260D3, SC261D SC260M, SC260M3, SC261M	V_{DRM}	200 400 600	Volts
RMS On-State Current	$I_T(RMS)$	25	Amps
Peak Non-Repetitive Surge Current (One Cycle, 60 Hz)	I_{TSM}	250	Amps
Circuit Fusing Considerations $t = 1 \text{ ms}$ $t = 8.3 \text{ ms}$	I^2t	150 260	A^2s
Peak Gate Power (Pulse Width = $10 \mu\text{s}$)	P_{GM}	10	Watts
Average Gate Power	$P_{G(AV)}$	0.5	Watt
Peak Gate Power	I_{GM}	2	Amps
Operating Junction Temperature Range	T_J	-40 to $+115$	$^\circ\text{C}$
Storage Temperature Range	T_{stg}	-40 to $+125$	$^\circ\text{C}$
Stud Torque	—	30	In. lb.

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Case SC260, SC261 SC260()3	$R_{\theta JC}$	1.8 1.95	$^\circ\text{C/W}$

**SC260
SC260()3
SC261**

**TRIACs
25 AMPERES RMS
200 thru 600 VOLTS**




SC260



SC261



SC260()3



NJ Semi-Conductors reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However, NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.

Quality Semi-Conductors

SC260 • SC260()3 • SC261

ELECTRICAL CHARACTERISTICS ($T_C = +25^\circ\text{C}$ unless otherwise noted. Values apply for either polarity of Main Terminal 2
Characteristics referenced to Main Terminal 1.)

Characteristic	Symbol	Min	Typ	Max	Unit
Peak Forward or Reverse Blocking Current (Rated V_{DRM} or V_{RRM} , gate open) $T_C = 25^\circ\text{C}$ $T_C = +115^\circ\text{C}$	I_{DRM}, I_{RRM}	— —	— —	10 1	μA mA
Peak On-State Voltage ($I_{TM} = 35\text{ A}$ Peak, Pulse Width = 1 ms, Duty Cycle $\leq 2\%$)	V_{TM}	—	—	1.58	Volts
Critical Rate of Rise of Off-State Voltage (Rated V_{DRM} , Gate Open-Circuited, Exponential Waveform) $T_C = +115^\circ\text{C}$	dv/dt	50	—	—	$\text{V}/\mu\text{s}$
Critical Rate-of-Rise of Commutating Off-State Voltage ($I_{T(RMS)} = \text{Rated RMS On-State Current}$) ($V_{DRM} = \text{Rated Peak Off-State Voltage}$, Gate Open-Circuited, Commutating $di/dt \approx 13.5\text{ A/ms}$) $T_C = +80^\circ\text{C}$	$dv/dt(c)$	5	—	—	$\text{V}/\mu\text{s}$
DC Gate Trigger Current (Continuous dc) ($V_D = 12\text{ Vdc}$) MT2(+), G(+); MT2(-), G(-); $R_L = 100\text{ Ohms}$ MT2(+), G(-); $R_L = 50\text{ Ohms}$	I_{GT}	— —	— —	50 50	mAdc
DC Gate Trigger Current (Continuous dc) ($V_D = 12\text{ Vdc}$) MT2(+), G(+); MT2(-), G(-); $R_L = 50\text{ Ohms}$ MT2(+), G(-); $R_L = 25\text{ Ohms}$ $T_C = -40^\circ\text{C}$	I_{GT}	— —	— —	80 80	mAdc
DC Gate Trigger Voltage (Continuous dc) ($V_D = 12\text{ Vdc}$) MT2(+), G(+); MT2(-), G(-); $R_L = 100\text{ Ohms}$ MT2(+), G(-); $R_L = 50\text{ Ohms}$	V_{GT}	— —	— —	2.5 2.5	Vdc
DC Gate Trigger Voltage (Continuous dc) ($V_D = 12\text{ Vdc}$) MT2(+), G(+); MT2(-), G(-); $R_L = 50\text{ Ohms}$ MT2(+), G(-); $R_L = 25\text{ Ohms}$ $T_C = -40^\circ\text{C}$	V_{GT}	— —	— —	3.5 3.5	Vdc
DC Gate Non-Trigger Voltage ($V_D = \text{Rated } V_{DRM}$, $R_L = 1\text{K Ohms}$, All Trigger Modes) $T_C = 115^\circ\text{C}$	V_{GD}	0.25	—	—	Vdc
Holding Current ($V_D = 24\text{ Vdc}$, Peak Initiating Current = 0.5 A, Pulse Width = 0.1 to 10 ms, Gate Trigger Source = 7 V, 20 Ohms) $T_C = +25^\circ\text{C}$ $T_C = -40^\circ\text{C}$	I_H	— —	— —	75 100	mAdc
Latching Current ($V_D = 24\text{ Vdc}$, Gate Trigger Source = 15 V, 100 Ohms, Pulse Width = 50 μs , 5 μs Maximum Rise and Fall Times) MT2(+), G(+); MT2(-), G(-) $T_C = 25^\circ\text{C}$ MT2(+), G(-) $T_C = 25^\circ\text{C}$ MT2(+), G(+); MT2(-), G(-) $T_C = -40^\circ\text{C}$ MT2(+), G(-) $T_C = -40^\circ\text{C}$	I_L	— — — —	— — — —	100 200 200 400	mAdc

